

Ideal for contract manufacturers and harness houses, Molex's easy-to-use, PT-1500 Bench-Top Wire Crimp Pull-Force Tester is designed with a single-stroke, pull-down lever to measure accurately the pull strength up to 978.61N (220 lbf) on a wide range of crimped terminals and wires

The Molex PT-1500 Bench-Top Wire Crimp Pull-Force Tester is a manual, lever-operated digital pull tester. The PT-1500 Bench-Top Wire Crimp Pull-Force Tester comes standard with two clamps to hold the wire. The wheel-type clamp and the clamp-style holder provide a broad range of clamping options, enabling customers to better analyze their wire-termination quality.

The PT-1500 Bench-Top Wire Crimp Pull-Force Tester is shipped with an AC rechargeable adapter for a 120V AC power supply. A 230V AC rechargeable adapter is available (part number 63801-9105). The PT-1500 Bench-Top Wire Crimp Pull-Force Tester can operate on internal rechargeable batteries or directly from the AC adapter.

FEATURES AND BENEFITS

- Manual, single-stroke, pull-down lever automatically grips the wire and accurately measures the crimp pull strength on a wide range of wire sizes and types including crimped, soldered or solderless wire terminals
- Manual, single-stroke, pull-down lever automatically grips the wire which eliminates the need for additional grips or accessories and minimizes set-up time
- Grips wire diameters up to 5.84mm (.230"), and wire gauges from 0.05 to 10.00mm² (8 to 30 AWG) reduces the need for multiple pull test machines
- Digital output is push-button selectable can be programmed to show pull-force data in multiple units, including lbf, kgf and Newtons, for use in the global marketplace
- Operates on internal rechargeable batteries or an AC adapter (120 or 230V AC) for use in equipment without a direct power source
- Wheel-type clamp has multiple slot sizes, for wire diameters up to 5.84mm (.230") allowing for different wire sizes to be used in the machine
- Clamp-style holder suitable for open-barrel products secures the front of the terminal body to achieve an accurate pull-force reading

MARKETS AND APPLICATIONS

- Automotive market
- Industrial market
- Commercial market
- Contract manufacturers
- Design / engineering facilities
- 8 to 30 AWG wire up to 978.61N (220 lbf or 99.8 kgf)

PT-1500 Bench-Top Wire Crimp Pull-Force Tester

63801 Pull-Force Tester 0.05 to 10.00mm² (8 to 30 AWG) Wire Range



Bench-Top Wire Crimp Pull-Force Tester
(tests crimped wires up to 978.61N (220 lbf or 99.79 kgf))

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81

Россия +7(495)268-04-70

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Псков (8112)59-10-37
Пермь (342)205-81-47
Казахстан +7(7172)727-132

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35
Киргизия +996(312)96-26-47

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Уда (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93

<https://molex.nt-rt.ru/> || mxd@nt-rt.ru

SPECIFICATIONS

Physical

Weight: 10.9kg (24 lbf)
Width: 475.0 to 545.0mm (18.70 to 21.45")
Depth: 150.0mm (5.90")
Height: 400.0mm (15.74")
Pull-Force: 978.61N (220 lbf or 99.8kg)

PT-1500 Bench-Top Wire Crimp Pull-Force Tester

63801 Pull-Force Tester 0.05 to 10.00mm² (8 to 30 AWG) Wire Range

ORDERING INFORMATION

Order No.	Component	Used With	Wire Range	Cable Diameter
63801-9100	PT-1500 Bench-Top Wire Crimp Pull-Force Tester	AWG or Metric Wire	0.05 to 10.00mm ² (8 to 30 AWG)	N/A

SUPPORTING PRODUCTS FOR REFERENCE

Order No.	Component	Used With	Wire Range	Cable Diameter
63801-9101	Multi-Terminal Grip for Closed-Barrel Equipment (standard with unit)	63801-9100	0.05 to 10.00mm ² (8 to 30 AWG) Cable	Up to 5.84mm (.230")
63801-9102	Clamp-Type Grip for Open-Barrel Equipment (standard with unit)	63801-9100	0.05 to 10.00mm ² (8 to 30 AWG) Cable	Up to 5.84mm (.230")
63801-9103	AC Power Adapter and charger, 120V AC (standard with unit)	120V AC	N/A	N/A
63801-9105	AC Power Adapter and Charger, 230V AC (standard with unit)	230V AC	N/A	N/A
63801-9104	Display module (standard with unit)	63801-9100	N/A	N/A

Алматы (7273)495-231
Ангарск (3955)60-70-56
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Благовещенск (4162)22-76-07
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Владикавказ (8672)28-90-48
Владимир (4922)49-43-18
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Коломна (4966)23-41-49
Кострома (4942)77-07-48
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Курган (3522)50-90-47
Липецк (4742)52-20-81
Россия +7(495)268-04-70

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Ноябрьск (3496)41-32-12
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Петрозаводск (8142)55-98-37
Пермь (8112)59-10-37
Пермь (342)205-81-47
Казахстан +7(7172)727-132

Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Саранск (8342)22-96-24
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Сыктывкар (8212)25-95-17
Тамбов (4752)50-40-97
Тверь (4822)63-31-35
Киргизия +996(312)96-26-47

Тольятти (8482)63-91-07
Томск (3822)98-41-53
Тула (4872)33-79-87
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Улан-Удэ (3012)59-97-51
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Чебоксары (8352)28-53-07
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Чита (3022)38-34-83
Якутск (4112)23-90-97
Ярославль (4852)69-52-93